



MX-9200

Mixer Pre-Amplifier



*Make parameter adjustments
wirelessly, conveniently*



The MX-9200 is a wireless mixer pre-amplifier ideal for function rooms, training rooms and even small-scale houses of worship. It's equipped with up to 9 inputs of which 4 inputs comes with phantom power. Parameter settings for Volume, Bass, Middle, Treble, Mute on individual input channel and 2 output channels can be controlled via an android touch screen device connected by bluetooth, bringing you the convenience to make adjustments there and then even when you are far away from the equipment.



Rear of MX-9200



Tablet image



Mobile phone image

* Images of MX-9200 app are only for illustration.

SPECIFICATIONS

	MX-9200
Power Source	AC 220 - 240 V, 14 W
Audio Input	Input CH 1 with Phantom option 19 V DC: - CHIME MIC: Balanced, Selectable sensitivity -55 dB (1.8 mV)/ -30 dB (30 mV), 2.2 kΩ, rated 1 kHz, RJ45 connector - MIC: Balanced, Selectable sensitivity -55 dB (1.8 mV)/ -30 dB (30 mV), 2.2 kΩ, rated 1 kHz, Phone jack connector Input CH 2-4 with Phantom option 19 V DC: - Balanced, Sensitivity -55 dB (1.8 mV), 2.2 kΩ, rated 1 kHz, Phone jack connector Selectable Input CH 5 with options: - MIC: Balanced, Sensitivity -55 dB (1.8 mV), 2.2 kΩ, rated 1 kHz, Phone jack connector - AUX: Unbalanced, Sensitivity 0 dB, 10 kΩ, rated 1 kHz, RCA jack connector Selectable Sensitivity Input CH 6-8, Removable terminal 3 pins with sensitivity options: - LINE: Balanced, Sensitivity 0 dB, 2.2 kΩ, rated 1 kHz - MIC: Balanced, Sensitivity -55 dB (1.8 mV), 2.2 kΩ, rated 1 kHz Selectable Sensitivity Input CH 9, Removable terminal 3 pins with sensitivity options: - MIC: Balanced, Sensitivity -55 dB (1.8 mV), 2.2 kΩ, rated 1 kHz - STREAMING: Unbalanced, Sensitivity 0 dB, 10 kΩ, rated 1 kHz
Audio Output	Audio OUT A & B, Balanced, Removable terminal 3 pins Optional output level: 0 dB / -10 dB (300 mV) / -20 dB (100 mv), 600 Ω, rated 1 kHz
Control Output	9 Shortcut switch IN, 2 Shortcut switch OUT, 1 Shortcut switch VOLUME, 1 Shortcut switch Tone Control, 1 Shortcut switch Input Selection, 1 Navigation switch (Right, Left, Push)
Tone Control	Bass ± 13 dB at 100 Hz, Middle ± 13 dB at 1 kHz, Treble ± 13 dB at 10 kHz
Distortion	Under 1% at 1 kHz, rated power
Frequency Response	30 Hz ~ 20 kHz, ± 3 dB
Indicator	LCD display with backlight green, POWER indicator (green), STATUS indicator (green), SIGNAL indicator (green), PEAK indicator (red)
Connection	Bluetooth 4.2, USB Type B (PC Setting/Update Firmware)
Finish	Front Panel: Aluminum Hair Line, Painting Black / Case: Steel Plate, Painting Black
Dimensions (W x H x D)	420 x 59 x 339.7 mm
Weight	3.3 kg
Accessories	6P connector x 2, 3P connector x 2



Like us on Facebook
facebook.com/TOAasiapacific

TOA
 Smiles for the Public

TOA Electronics Pte Ltd
www.toa.com.sg

Specifications are subject to change without notice.
 Printed in Singapore (65) 865-0421-01