

Loudspeaker Cont roller

EQ-31



Introduction:

The role of equalizer in a sound processing system can not be underestimated. Different environment will definitely affect the performance of a sound processing system . It is recommended that a equalizer should be equipped in your system. SOUNDKING products EQ-31 is your optimal choice. EQ-31 is a dual 31 segment graphic equalizer according to ISO 1/3 otc for its 20Hz- 20kHz frequency.

Features

- > Stable performance.
- > The excellency of ratio performance is well recognized in domestic and overseas market.
- > Compact and convenient.
- > CE & ETL certificated for safety.
- > Transformer balanced output.

Application

Theater, disco, studio, concert, stage show, etc.

Central F requency(Hz)	Low Cut Filter	Range (Optional)	Weight
20, 25, 31.5, 40, 50, 63, 80, 100, 125, 160, 200, 250, 315, 400, 500, 630, 800,1k, 1.25k, 1.6k, 2k, 2.5k, 3.15k, 4k, 5k,6.3k, 8k, 10k, 12.5k, 16k, 20k(Hz)	40Hz (-12 dB/oct)	±6dB/±15dB(switchable)	3kg

Connector Power	Consumption	Dimension
XLR bal L/R, TRS 1/4" bal input L/R, XLR bal output L/R, TRS 1/4" bal output L/R	17W (AC100~240 V, 50~60Hz)	433x183x88mm